

# Unity Connection

## Voicemail Menu Options



- press 1 to play new message
  - 1 - save
  - 4 - repeat
- press 2 + 1 to play saved messages
  - 5 - skip back
  - 7 - delete
- press 2 + 2 to play deleted messages
  - 9 - play message properties
  - record a message at the tone

- press 4 to send messages
  - choose recipient
    - # + # switch selection mode (extension, name)
    - 1 - repeat name
    - 7 - previous name
    - 9 - next name
    - # - choose name
  - set delivery options
    - 1 - mark urgent
    - 2 - request read receipt
    - 3 - mark urgent
  - review message
    - 5 - review message
    - 6 - re-record message
    - 7 - add to message
  - change recipients
    - 9 + 1 add a recipient
    - 9 + 2 review or delete recipients
    - 9 + 5 copy self
  - press 4 to setup future delivery
    - 0 - deliver today
      - enter HHMM, press #
    - [1-8] - deliver [x] days from now
      - enter 1 for AM, 2 for PM
    - 9 - setup month and day
      - enter 2- digit month, press #
      - enter 2- digit day (1-30), press #
      - enter 1 for AM, 2 for PM
  - press # to send

- press 5 for setup options
  - press 1 to manage greetings
    - 1 - re-record current greeting
    - 2 -toggle alternate greeting
      - 1 - set end date and time
      - # - leave on indefinitely
    - 3 - to edit other greetings
      - 1 - standard greeting
      - 2 - closed greeting
      - 3 - alternate greeting
      - 4 - busy greeting
      - 5 - internal greeting
      - 6 - holiday greeting
    - 4 - to play all greetings

- press 5 for setup options
  - press 2 to change message settings
    - 1 - notification settings
      - 1 - pager
        - 1 - turn on
      - 2 - home phone
        - 2 - review settings
      - 3 - work phone
        - 3 - change number
      - 4 - mobile phone
    - 3 - toggle brief/verbose menu style
    - 4 - manage private lists
      - 1 - hear private lists
      - 2 - change list members
        - 1 - add name
        - 2 - review and delete names
      - 3 - change list names

- press 5 for setup options
  - press 3 to manage preferences
    - 1 - change PIN
      - enter new 5-digit PIN, press pound (#)
      - enter PIN again to confirm, press pound (#)
    - 2 - change recorded name
      - \* - keep recorded name
      - # - End Recording
      - 1 - re-record name
    - 3 - change directory listing
      - feature disabled. contact sysadmen

- press 4 to change transfer rules
  - 1 - change STD transfer rule
    - 1 - enable rule
  - 2 - change ALT transfer rule
    - 2 - send callers to voicemail or extension
  - 1 - change CLOSED transfer rule
    - 3 - change transfer number

press 9 to transfer to another number